

6L6 Spalted Alder Parts List

Item Number	Quantity	Part
1	2	Vacuum Tube - 6L6
2	1	Vacuum Tube - 6SL7
3	1	Vacuum Tube - GZ34
4	1	Transformer - Edcor XPWR178-120 - 660vCT@200mA, 5v@3A, 6.3v@6A
5	1	Choke - Triad C-14X - 6H 200mA
6	2	Choke - Hammond 154M - 2H 100mA
7	2	Transformer - Edcor GXSE15-5K 8Ω
8	4	Tube Socket - 8 Pin Octal (high temperature type preferred)
9	1	Fuse holder - 3AG type - panel mount
10	1	Switch - SPST 125VAC 1A - toggle - panel mount
11	1	IEC Power connector - Qualtek 703W-00/08 or equiv.
12	1	IEC Power cord - 6ft 18AWG - NEMA 5-15P TO IEC320C13
13	2	Dual binding posts - 5 way - Pomona 6883 or equiv.
14	2	RCA jack - panel mount - REAN / Neutrik NYS367-0 or equiv.
15	1	Front Panel Indicator Light - Panel mount - 609722124591 or equiv.
16	1	Panel Lamp Jewel Lens - 609722124621 or equiv.
17	1	#44 Panel lamp (6.3V)
18	1	Potentiometer - 50Ω 5W Linear Taper - 1/4" shaft - panel mount
19	1	Potentiometer - Dual 100kΩ audio taper (A) - 1/4" shaft - panel mount
20	2	Knob - for 1/4" shaft - set screw
21	2	Capacitor - Electrolytic - 30μf@500v - JJ ANH series or equiv.
22	3	Capacitor - Electrolytic - 100μf@500v - JJ ANH series or equiv.
23	2	Capacitor - Electrolytic - 470μf@50v
24	2	Capacitor - Electrolytic - 100μf@50v
25	2	Capacitor - 0.1μf polypropylene - Sprague 716 series or equiv.
26	4	Resistor 2kΩ 1/2W 1% Metal Film
27	2	Resistor 100kΩ 1/2W 1% Metal Film
28	1	Resistor 20kΩ 1/2W 1% Metal Film
29	3	Resistor 470kΩ 1/2W 1% Metal Film
30	2	Resistor 470Ω 5W 1% Wirewound - Vishay RS005470R0FB12 or equiv.
31	1	Fuse - 3AG - 1A 250V
32	1	Terminal Strip - 4 Lug, 2nd Lug Common, Horizontal
33	13	Terminal Strip - 5 Lug, 3rd Lug Common, Horizontal
34	1	Terminal Strip - 3 Lug, 2nd Lug Common, Horizontal
35	1	14Ga solid Cu wire, bare, 25"